


## 3 band car audio processor

### Features

- Input multiplexer
  - QD1: quasi-differential stereo inputs
  - SE1: stereo single-ended input
  - SE2: stereo single-ended input
  - SE3: stereo single-ended input
  - FD1 / SE4+SE5: 1 full-differential input or 2 stereo single-ended inputs
- Loudness
  - 2<sup>nd</sup> order frequency response
  - Programmable center frequency (400 Hz / 800 Hz / 2400 Hz)
  - 15 dB with 1 dB steps
  - Selectable high frequency boost
  - Selectable flat-mode (constant attenuation)
- Volume
  - +23 dB to -31 dB with 1 dB step resolution
  - Soft-step control with programmable blend times
- Bass
  - 2<sup>nd</sup> order frequency response
  - Center frequency programmable in 4 steps (60 Hz / 80 Hz / 100 Hz / 200 Hz)
  - Q programmable 1.0/1.25/1.5/2.0
  - DC gain programmable
  - -15 dB to 15 dB range with 1 dB resolution
- Middle
  - 2<sup>nd</sup> order frequency response
  - Center frequency programmable in 4 steps (500 Hz / 1 kHz / 1.5 kHz / 2.5 kHz)
  - Q programmable 0.75/1.0/1.25
  - -15 dB to 15 dB range with 1 dB resolution
- Treble
  - 2<sup>nd</sup> order frequency response (10 kHz / 12.5 kHz / 15 kHz / 17.5 kHz)
  - Center frequency programmable in 4 steps (10 kHz / 12.5 kHz / 15 kHz / 17.5 kHz)
  - -15 dB to 15 dB with 1 dB resolution



- Speaker
  - 4 independent soft step speaker controls
  - +15 dB to -79 dB with 1 dB steps
  - Direct mute
- Subwoofer
  - 2<sup>nd</sup> order low pass filter with programmable cut off frequency (55 Hz / 85 Hz / 120 Hz / 160 Hz)
  - 2 independent soft step level control, +15 dB to -79 dB with 1 dB steps
- Mute functions
  - Direct mute
  - Digitally controlled SoftMute with 4 programmable mute-times (0.48 ms/0.96 ms/8 ms/16 ms)
- Offset detection
  - Offset voltage detection circuit for on-board power amplifier failure diagnosis

### Description

The TDA7718N is a high performance signal processor specifically designed for car radio applications. The device includes a high performance audioprocessor with fully integrated audio filters and new Soft Step architecture. The digital control allows programming in a wide range of filter characteristics.

**Table 1. Device summary**

| Order code | Package | Packing       |
|------------|---------|---------------|
| TDA7718N   | TSSOP28 | Tube          |
| TDA7718NTR | TSSOP28 | Tape and reel |

# Contents

- 1      Block circuit diagram ..... 6**
- 2      Pin connection and pin description ..... 7**
  - 2.1    Pin connection ..... 7
  - 2.2    Pin description ..... 7
- 3      Electrical specifications ..... 9**
  - 3.1    Thermal data ..... 9
  - 3.2    Absolute maximum ratings ..... 9
  - 3.3    Electrical characteristics ..... 9
- 4      Description of the audioprocessor ..... 13**
  - 4.1    Input stages ..... 13
    - 4.1.1    Quasi-differential stereo input (QD1) ..... 13
    - 4.1.2    Single-ended stereo input (SE1, SE2, SE3) ..... 13
    - 4.1.3    Full-differential stereo input or single-ended input (FD1/QD2/SE4+SE5) 13
  - 4.2    Loudness ..... 15
    - 4.2.1    Loudness attenuation ..... 15
    - 4.2.2    Peak frequency ..... 15
    - 4.2.3    High frequency boost ..... 16
    - 4.2.4    Flat mode ..... 16
  - 4.3    SoftMute ..... 17
  - 4.4    SoftStep volume ..... 17
  - 4.5    Bass ..... 18
    - 4.5.1    Bass attenuation ..... 18
    - 4.5.2    Bass center frequency ..... 18
    - 4.5.3    Quality factors ..... 19
    - 4.5.4    DC mode ..... 19
  - 4.6    Middle ..... 20
    - 4.6.1    Middle attenuation ..... 20
    - 4.6.2    Middle center frequency ..... 20
    - 4.6.3    Quality factors ..... 21
  - 4.7    Treble ..... 21

---

|          |                                                 |           |
|----------|-------------------------------------------------|-----------|
| 4.7.1    | Treble attenuation                              | 21        |
| 4.7.2    | Center frequency                                | 22        |
| 4.8      | Subwoofer filter                                | 22        |
| 4.9      | Softstep control                                | 23        |
| 4.10     | DC offset detector                              | 23        |
| 4.11     | Audioprocessor testing                          | 25        |
| <b>5</b> | <b>I<sup>2</sup>C bus specification</b>         | <b>26</b> |
| 5.1      | Interface protocol                              | 26        |
| 5.2      | I <sup>2</sup> C bus electrical characteristics | 26        |
| 5.2.1    | Receive mode                                    | 27        |
| 5.2.2    | Transmission mode                               | 27        |
| 5.2.3    | Reset condition                                 | 27        |
| 5.3      | Data byte specification                         | 29        |
| <b>6</b> | <b>Package information</b>                      | <b>38</b> |
| <b>7</b> | <b>Revision history</b>                         | <b>39</b> |

## List of tables


|           |                                                             |    |
|-----------|-------------------------------------------------------------|----|
| Table 1.  | Device summary . . . . .                                    | 1  |
| Table 2.  | Pin description . . . . .                                   | 7  |
| Table 3.  | Thermal data . . . . .                                      | 9  |
| Table 4.  | Absolute maximum ratings . . . . .                          | 9  |
| Table 5.  | Electrical characteristics . . . . .                        | 9  |
| Table 6.  | I <sup>2</sup> C bus electrical characteristics . . . . .   | 26 |
| Table 7.  | Subaddress (receive mode) . . . . .                         | 28 |
| Table 8.  | Main selector (0) . . . . .                                 | 29 |
| Table 9.  | Soft mute / others (4) . . . . .                            | 30 |
| Table 10. | SoftStep I (5) . . . . .                                    | 31 |
| Table 11. | SoftStep II / DC detector (6) . . . . .                     | 32 |
| Table 12. | Loudness (7) . . . . .                                      | 33 |
| Table 13. | Volume / output gain (8) . . . . .                          | 33 |
| Table 14. | Treble filter (9) . . . . .                                 | 34 |
| Table 15. | Middle filter (10) . . . . .                                | 34 |
| Table 16. | Bass filter (11) . . . . .                                  | 35 |
| Table 17. | Subwoofer / middle / bass (12) . . . . .                    | 35 |
| Table 18. | Speaker attenuation (FL/FR/RL/RR/SWL/SWR) (13-18) . . . . . | 36 |
| Table 19. | Testing audio processor 1 (19) . . . . .                    | 36 |
| Table 20. | Testing audio processor 2 (20) . . . . .                    | 37 |
| Table 21. | Testing audio processor 3 (21) . . . . .                    | 37 |
| Table 22. | Document revision history . . . . .                         | 39 |

## List of figures

|            |                                                                 |    |
|------------|-----------------------------------------------------------------|----|
| Figure 1.  | Block circuit diagram. . . . .                                  | 6  |
| Figure 2.  | Pin connection (top view) . . . . .                             | 7  |
| Figure 3.  | FD / QD / SE block diagram . . . . .                            | 14 |
| Figure 4.  | Loudness attenuation @ $f_P = 400$ Hz. . . . .                  | 15 |
| Figure 5.  | Loudness center frequencies @ attn. = 15 dB. . . . .            | 15 |
| Figure 6.  | Loudness attenuation, $f_C = 2.4$ kHz. . . . .                  | 16 |
| Figure 7.  | SoftMute timing. . . . .                                        | 17 |
| Figure 8.  | Bass control @ $f_C = 80$ Hz, $Q = 1$ . . . . .                 | 18 |
| Figure 9.  | Bass center frequencies @ gain = 14 dB, $Q = 1$ . . . . .       | 18 |
| Figure 10. | Bass quality factors @ gain = 14 dB, $f_C = 80$ Hz . . . . .    | 19 |
| Figure 11. | Bass normal and DC mode @ gain = 14 dB, $f_C = 80$ Hz . . . . . | 19 |
| Figure 12. | Middle control @ $f_C = 1$ kHz, $Q = 1$ . . . . .               | 20 |
| Figure 13. | Middle center frequencies @ gain = 14 dB, $Q = 1$ . . . . .     | 20 |
| Figure 14. | Middle quality factors @ gain = 14 dB, $f_C = 1$ kHz . . . . .  | 21 |
| Figure 15. | Treble control @ $f_C = 17.5$ kHz. . . . .                      | 21 |
| Figure 16. | Treble center frequencies @ gain = 14 dB. . . . .               | 22 |
| Figure 17. | Subwoofer cut frequencies . . . . .                             | 22 |
| Figure 18. | DC offset detection circuit (simplified) . . . . .              | 24 |
| Figure 19. | Test circuit . . . . .                                          | 25 |
| Figure 20. | I <sup>2</sup> C bus interface protocol . . . . .               | 26 |
| Figure 21. | I <sup>2</sup> C bus data . . . . .                             | 27 |
| Figure 22. | TSSOP28 mechanical data and package dimensions . . . . .        | 38 |

# 1 Block circuit diagram


Figure 1. Block circuit diagram



## 2 Pin connection and pin description

### 2.1 Pin connection

Figure 2. Pin connection (top view)



### 2.2 Pin description

Table 2. Pin description

| No. | Pin name        | Description                                                                        | I/O |
|-----|-----------------|------------------------------------------------------------------------------------|-----|
| 1   | SE1L            | Single-end input left                                                              | I   |
| 2   | SE1R            | Single-end input right                                                             | I   |
| 3   | SE2L            | Single-end input left                                                              | I   |
| 4   | SE2R            | Single-end input right                                                             | I   |
| 5   | SE3L            | Single-end input left                                                              | I   |
| 6   | SE3R            | Single-end input right                                                             | I   |
| 7   | QD1L            | quasi-differential stereo inputs left                                              | I   |
| 8   | QD1G            | quasi-differential stereo inputs common                                            | I   |
| 9   | QD1R            | quasi-differential stereo inputs right                                             | I   |
| 10  | FD1L+/QD2L/SE4L | Full differential + input left or quasi-differential left or single-end input left | I   |

Table 2. Pin description (continued)

| No. | Pin name        | Description                                                                           | I/O |
|-----|-----------------|---------------------------------------------------------------------------------------|-----|
| 11  | FD1L-/QD2G/SE4R | Full differential - input left or quasi-differential ground or single-end input right | I   |
| 12  | FD1R-/QD2G/SE5L | Full differential - input right or quasi-differential ground or single-end input left | I   |
| 13  | FD1R+/QD2R/SE5R | Full differential + input right or quasi-differential right or single-end input right | I   |
| 14  | CREF            | Reference capacitor                                                                   | O   |
| 15  | GND             | Ground                                                                                | S   |
| 16  | OUTSWR          | Subwoofer right output                                                                | O   |
| 17  | OUTSWL          | Subwoofer left output                                                                 | O   |
| 18  | OUTRF           | Front right output                                                                    | O   |
| 19  | OUTRR           | Rear right output                                                                     | O   |
| 20  | OUTLR           | Rear left output                                                                      | O   |
| 21  | OUTLF           | Front left output                                                                     | O   |
| 22  | WinTC           | DC offset detector filter output                                                      | O   |
| 23  | MUTE            | External mute pin                                                                     | I   |
| 24  | VCC             | Supply                                                                                | S   |
| 25  | SCL             | I <sup>2</sup> C bus clock                                                            | I   |
| 26  | SDA             | I <sup>2</sup> C bus data                                                             | I/O |
| 27  | DC_ERR          | DC offset detector output                                                             | O   |
| 28  | WIN_IN          | DC offset detector input                                                              | I   |



## 3 Electrical specifications

### 3.1 Thermal data

Table 3. Thermal data

| Symbol          | Description                            | Value | Unit |
|-----------------|----------------------------------------|-------|------|
| $R_{th-j\ amb}$ | Thermal resistance junction-to-ambient | 114   | °C/W |

### 3.2 Absolute maximum ratings

Table 4. Absolute maximum ratings

| Symbol        | Parameter                             | Value      | Unit |
|---------------|---------------------------------------|------------|------|
| $V_S$         | Operating supply voltage              | 10.5       | V    |
| $V_{in\_max}$ | Maximum voltage for signal input pins | 7          | V    |
| $T_{amb}$     | Operating ambient temperature         | -40 to 85  | °C   |
| $T_{stg}$     | Storage temperature range             | -55 to 150 | °C   |

### 3.3 Electrical characteristics

$V_S = 8.5\text{ V}$ ;  $T_{amb} = 25\text{ °C}$ ;  $R_L = 10\text{ k}\Omega$ ; all gains = 0 dB;  $f = 1\text{ kHz}$ ; unless otherwise specified

Table 5. Electrical characteristics

| Symbol                            | Parameter                                   | Test condition                              | Min. | Typ. | Max. | Unit          |
|-----------------------------------|---------------------------------------------|---------------------------------------------|------|------|------|---------------|
| <b>Supply</b>                     |                                             |                                             |      |      |      |               |
| $V_S$                             | Supply voltage                              | -                                           | 7.5  | 8.5  | 10   | V             |
| $I_S$                             | Supply current                              | -                                           | 23   | 29   | 35   | mA            |
| <b>Input selector</b>             |                                             |                                             |      |      |      |               |
| $R_{in}$                          | Input resistance                            | All single ended inputs                     | 70   | 100  | 130  | k $\Omega$    |
| $V_{CL}$                          | Clipping level                              | Input gain = 0 dB                           | 2    | -    | -    | $V_{RMS}$     |
| $S_{IN}$                          | Input separation                            | -                                           | -    | 95   | -    | dB            |
| <b>Differential stereo inputs</b> |                                             |                                             |      |      |      |               |
| $R_{in}$                          | Input resistance                            | Differential                                | 70   | 100  | -    | k $\Omega$    |
| CMRR                              | Common mode rejection ratio for main source | $V_{CM} = 1\text{ V}_{RMS}$ @ 1 kHz         | 44   | 60   | -    | dB            |
|                                   |                                             | $V_{CM} = 1\text{ V}_{RMS}$ @ 10 kHz        | 44   | 60   | -    | dB            |
| $e_{No}$                          | Output noise @ speaker outputs              | 20 Hz - 20 kHz, A-weighted; all stages 0 dB | -    | 12   | 22   | $\mu\text{V}$ |

**Table 5. Electrical characteristics (continued)**

| Symbol                  | Parameter                 | Test condition              | Min.      | Typ.      | Max.      | Unit       |
|-------------------------|---------------------------|-----------------------------|-----------|-----------|-----------|------------|
| <b>Loudness control</b> |                           |                             |           |           |           |            |
| $A_{MAX}$               | Max attenuation           | -                           | 14        | 15        | 16        | dB         |
| $A_{STEP}$              | Step resolution           | -                           | 0.5       | 1         | 1.5       | dB         |
| $f_{Peak}$              | Peak frequency            | $f_{P1}$                    | -         | 400       | -         | Hz         |
|                         |                           | $f_{P2}$                    | -         | 800       | -         | Hz         |
|                         |                           | $f_{P3}$                    | -         | 2400      | -         | Hz         |
| <b>Volume control</b>   |                           |                             |           |           |           |            |
| $G_{MAX}$               | Max gain                  | -                           | 22        | 23        | 24        | dB         |
| $A_{MAX}$               | Max attenuation           | -                           | -         | -31       | -30       | dB         |
| $A_{STEP}$              | Step resolution           | -                           | 0.5       | 1         | 1.5       | dB         |
| $E_A$                   | Attenuation set error     | -                           | -0.75     | 0         | +0.75     | dB         |
| $E_T$                   | Tracking error            | -                           | -         | -         | 2         | dB         |
| $V_{DC}$                | DC steps                  | Adjacent attenuation steps  | -3        | 0.1       | 3         | mV         |
|                         |                           | From 0 dB to $G_{MIN}$      | -5        | 0.5       | 5         | mV         |
| <b>Soft mute</b>        |                           |                             |           |           |           |            |
| $A_{MUTE}$              | Mute attenuation          | -                           | 80        | 100       | -         | dB         |
| $T_D$                   | Delay time                | T1                          | 0.35      | 0.48      | 0.65      | ms         |
|                         |                           | T2                          | 0.7       | 0.96      | 1.3       | ms         |
|                         |                           | T3                          | 5.6       | 7.6       | 9.6       | ms         |
|                         |                           | T4                          | 12.3      | 15.3      | 18.3      | ms         |
| $V_{TH\ Low}$           | Low threshold for SM pin  | -                           | -         | -         | 1         | V          |
| $V_{TH\ High}$          | High threshold for SM pin | -                           | 2.5       | -         | -         | V          |
| $R_{PU}$                | Internal pull-up resistor | -                           | 32        | 45        | 58        | k $\Omega$ |
| $V_{PU}$                | Internal pull-up voltage  | -                           | 3         | 3.3       | 3.6       | V          |
| <b>Bass control</b>     |                           |                             |           |           |           |            |
| $F_c$                   | Center frequency          | $f_{C1}$                    | -         | 60        | -         | Hz         |
|                         |                           | $f_{C2}$                    | -         | 80        | -         | Hz         |
|                         |                           | $f_{C3}$                    | -         | 100       | -         | Hz         |
|                         |                           | $f_{C4}$                    | -         | 200       | -         | Hz         |
| $Q_{BASS}$              | Quality factor            | $Q_1$                       | -         | 1         | -         | -          |
|                         |                           | $Q_2$                       | -         | 1.25      | -         | -          |
|                         |                           | $Q_3$                       | -         | 1.5       | -         | -          |
|                         |                           | $Q_4$                       | -         | 2         | -         | -          |
| $C_{RANGE}$             | Control range             | -                           | $\pm 14$  | $\pm 15$  | $\pm 16$  | dB         |
| $A_{STEP}$              | Step resolution           | -                           | 0.5       | 1         | 1.5       | dB         |
| $DC_{GAIN}$             | Bass-DC-gain              | DC = off                    | -1        | 0         | +1        | dB         |
|                         |                           | DC = on, gain = $\pm 15$ dB | $\pm 4.3$ | $\pm 4.7$ | $\pm 5.1$ | dB         |

Table 5. Electrical characteristics (continued)

| Symbol                     | Parameter                | Test condition             | Min. | Typ. | Max. | Unit             |
|----------------------------|--------------------------|----------------------------|------|------|------|------------------|
| <b>Middle control</b>      |                          |                            |      |      |      |                  |
| C <sub>RANGE</sub>         | Control range            | -                          | ±14  | ±15  | ±16  | dB               |
| A <sub>STEP</sub>          | Step resolution          | -                          | 0.5  | 1    | 1.5  | dB               |
| f <sub>c</sub>             | Center frequency         | f <sub>C1</sub>            | -    | 500  | -    | Hz               |
|                            |                          | f <sub>C2</sub>            | -    | 1    | -    | kHz              |
|                            |                          | f <sub>C3</sub>            | -    | 1.5  | -    | kHz              |
|                            |                          | f <sub>C4</sub>            | -    | 2.5  | -    | kHz              |
| Q <sub>MIDDLE</sub>        | Quality factor           | Q <sub>1</sub>             | -    | 0.75 | -    | -                |
|                            |                          | Q <sub>2</sub>             | -    | 1    | -    | -                |
|                            |                          | Q <sub>3</sub>             | -    | 1.25 | -    | -                |
| <b>Treble control</b>      |                          |                            |      |      |      |                  |
| C <sub>RANGE</sub>         | Clipping level           | -                          | ±14  | ±15  | ±16  | dB               |
| A <sub>STEP</sub>          | Step resolution          | -                          | 0.5  | 1    | 1.5  | dB               |
| f <sub>c</sub>             | Center frequency         | f <sub>C1</sub>            | -    | 10   | -    | kHz              |
|                            |                          | f <sub>C2</sub>            | -    | 12.5 | -    | kHz              |
|                            |                          | f <sub>C3</sub>            | -    | 15   | -    | kHz              |
|                            |                          | f <sub>C4</sub>            | -    | 17.5 | -    | kHz              |
| <b>Speaker attenuators</b> |                          |                            |      |      |      |                  |
| G <sub>MAX</sub>           | Max gain                 | -                          | 14   | 15   | 16   | dB               |
| A <sub>MAX</sub>           | Max attenuation          | -                          | -    | -79  | -74  | dB               |
| A <sub>STEP</sub>          | Step resolution          | -                          | 0.5  | 1    | 1.5  | dB               |
| A <sub>MUTE</sub>          | Mute attenuation         | -                          | 80   | 90   | -    | dB               |
| E <sub>E</sub>             | Attenuation set error    | -                          | -    | -    | 2    | dB               |
| V <sub>DC</sub>            | DC steps                 | Adjacent attenuation steps | -    | 0.1  | 5    | mV               |
| <b>Audio outputs</b>       |                          |                            |      |      |      |                  |
| V <sub>CL</sub>            | Clipping level           | d = 0.3 %; byte8_D6=1      | 2    | -    | -    | V <sub>RMS</sub> |
|                            |                          | d = 1 %; byte8_D6=0        | 2.2  | -    | -    | V <sub>RMS</sub> |
| R <sub>OUT</sub>           | Output impedance         | -                          | -    | 30   | 100  | Ω                |
| R <sub>L</sub>             | Output load resistance   | -                          | 2    | -    | -    | kΩ               |
| C <sub>L</sub>             | Output load capacitor    | -                          | -    | -    | 10   | nF               |
| V <sub>DC</sub>            | DC voltage level         | -                          | 3.8  | 4.0  | 4.2  | V                |
| <b>Subwoofer lowpass</b>   |                          |                            |      |      |      |                  |
| f <sub>LP</sub>            | Lowpass corner frequency | f <sub>LP1</sub>           | -    | 55   | -    | Hz               |
|                            |                          | f <sub>LP2</sub>           | -    | 85   | -    | Hz               |
|                            |                          | f <sub>LP3</sub>           | -    | 120  | -    | Hz               |
|                            |                          | f <sub>LP4</sub>           | -    | 160  | -    | Hz               |

Table 5. Electrical characteristics (continued)

| Symbol                             | Parameter                     | Test condition                                    | Min. | Typ. | Max. | Unit |
|------------------------------------|-------------------------------|---------------------------------------------------|------|------|------|------|
| <b>DC offset detection circuit</b> |                               |                                                   |      |      |      |      |
| $V_{th}$                           | Zero comp. window size        | V1                                                | ±10  | ±25  | ±40  | mV   |
|                                    |                               | V2                                                | ±30  | ±50  | ±70  | mV   |
|                                    |                               | V3                                                | ±50  | ±75  | ±100 | mV   |
|                                    |                               | V4                                                | ±70  | ±100 | ±130 | mV   |
| $t_{sp}$                           | Max rejected spike length     | -                                                 | 2    | 11   | 30   | µs   |
|                                    |                               | -                                                 | 5    | 22   | 50   | µs   |
|                                    |                               | -                                                 | 10   | 33   | 70   | µs   |
|                                    |                               | -                                                 | 15   | 44   | 90   | µs   |
| $I_{CHDCerr}$                      | DCErr charge current          | -                                                 | 2    | 5    | 8    | µA   |
| $I_{DISDCerr}$                     | DCErr discharge current       | -                                                 | 4    | 5    | 9    | mA   |
| $V_{OutH}$                         | DCErr high voltage            | -                                                 | 3    | 3.3  | 3.6  | V    |
| $V_{OutL}$                         | DCErr low voltage             | -                                                 | -    | 100  | 300  | mV   |
| <b>General</b>                     |                               |                                                   |      |      |      |      |
| $e_{NO}$                           | Output noise                  | BW=20 Hz to 20 kHz A-Weighted, all gain = 0 dB    | -    | 12   | 22   | µV   |
|                                    |                               | BW=20 Hz - 20 kHz A-Weighted, Output muted        | -    | 7    | 12   | µV   |
| S/N                                | Signal to noise ratio         | all gain = 0 dB, A-weighted;<br>$V_o = 2 V_{RMS}$ | 98   | 104  | -    | dB   |
| D                                  | Distortion                    | $V_{IN} = 1 V_{RMS}$ ; all stages 0 dB            | -    | 0.01 | 0.1  | %    |
| $S_C$                              | Channel separation left/right | -                                                 | -    | 90   | -    | dB   |

## 4 Description of the audioprocessor

### 4.1 Input stages

One quasi-differential stereo input, one full-differential stereo input and maximum five single-ended inputs are available.

#### 4.1.1 Quasi-differential stereo input (QD1)

The QD input is implemented as a buffered quasi-differential stereo stage with 100 k $\Omega$  input-impedance at each input. There is -3 dB attenuation at QD input stage.


#### 4.1.2 Single-ended stereo input (SE1, SE2, SE3)

The input-impedance at each input is 100 k $\Omega$  and the attenuation is fixed to -3 dB for incoming signals.

#### 4.1.3 Full-differential stereo input or single-ended input (FD1/QD2/SE4+SE5)

This device provides a full-differential stereo input stage (FD1) or 2<sup>nd</sup> quasi-differential stereo input stage. The full differential is a buffered full-differential stereo stage with 100 k $\Omega$  input-impedance at each input. When using as QD2 application, it needs to connect the two QD2G pins together from external and the input impedance at QDG becomes 50 k $\Omega$ . This stage can be also configured as 2 single-ended stereo input stages (SE4 and SE5). The configuration is done with the input selector control bits and the selection of FD1 and QD2 is controlled by a separate bit. There is -3 dB attenuation at the input stage. [Figure 3](#) shows the block diagram of this input stage.

Figure 3. FD / QD / SE block diagram




## 4.2 Loudness

There are four parameters programmable in the loudness stage.

### 4.2.1 Loudness attenuation

Figure 4 shows the attenuation as a function of frequency at  $f_p = 400$  Hz.


Figure 4. Loudness attenuation @  $f_p = 400$  Hz.



### 4.2.2 Peak frequency

Figure 5 shows the four possible peak-frequencies at 400, 800 and 2400 Hz.


Figure 5. Loudness center frequencies @ attn. = 15 dB.



### 4.2.3 High frequency boost

*Figure 6* shows the different Loudness shapes in low and high frequency boost.

**Figure 6.** Loudness attenuation,  $f_c = 2.4$  kHz



### 4.2.4 Flat mode

In flat mode the loudness stage works as a 0 dB to -15 dB attenuator.




### 4.3 SoftMute

The digitally controlled SoftMute stage allows muting/demuting the signal with a I<sup>2</sup>C bus programmable slope. The mute process can either be activated by the SoftMute pin or by the I<sup>2</sup>C bus. This slope is realized in a special S-shaped curve to mute slow in the critical regions (see [Figure 7](#)).

For timing purposes the bit 0 of the I<sup>2</sup>C bus output register is set to 1 from the start of muting until the end of demuting.

**Figure 7. SoftMute timing**



*Note:* Please notice that a started mute-action is always terminated and could not be interrupted by a change of the mute –signal.

### 4.4 SoftStep volume

When the volume-level is changed audible clicks could appear at the output. The root cause of those clicks could either be a DC-offset before the volume-stage or the sudden change of the envelope of the audio signal. With the SoftStep-feature both kinds of clicks could be reduced to a minimum and are no more audible. The blend-time from one step to the next is programmable as 5 ms or 10 ms. The SoftStep control is described in detail in [Chapter 4.9](#).


## 4.5 Bass

There are four parameters programmable in the bass stage:

### 4.5.1 Bass attenuation

*Figure 8* shows the attenuation as a function of frequency at a center frequency of 80 Hz.


**Figure 8. Bass control @  $f_C = 80$  Hz,  $Q = 1$**



### 4.5.2 Bass center frequency

*Figure 9* shows the four possible center frequencies 60, 80, 100 and 200 Hz.


**Figure 9. Bass center frequencies @ gain = 14 dB,  $Q = 1$**



### 4.5.3 Quality factors

Figure 10 shows the four possible quality factors 1, 1.25, 1.5 and 2.


**Figure 10. Bass quality factors @ gain = 14 dB,  $f_C = 80$  Hz**



### 4.5.4 DC mode

In this mode the DC-gain is increased by 4.4 dB. In addition the programmed center frequency and quality factor is decreased by 25 % which can be used to reach alternative center frequencies or quality factors.

**Figure 11. Bass normal and DC mode @ gain = 14 dB,  $f_C = 80$  Hz**



1. The center frequency, Q and DC-mode can be set fully independently.


## 4.6 Middle

There are three parameters programmable in the middle stage:

### 4.6.1 Middle attenuation

Figure 12 shows the attenuation as a function of frequency at a center frequency of 1 kHz.


Figure 12. Middle control @  $f_C = 1 \text{ kHz}$ ,  $Q = 1$



### 4.6.2 Middle center frequency

Figure 13 shows the four possible center frequencies 500 Hz, 1 kHz, 1.5 kHz and 2.5 kHz.


Figure 13. Middle center frequencies @ gain = 14 dB,  $Q = 1$



### 4.6.3 Quality factors

Figure 14 shows the three possible quality factors 0.75, 1 and 1.25.

**Figure 14. Middle quality factors @ gain = 14 dB,  $f_C = 1$  kHz**




## 4.7 Treble

There are two parameters programmable in the treble stage:

### 4.7.1 Treble attenuation

Figure 15 shows the attenuation as a function of frequency at a center frequency of 17.5 kHz.


**Figure 15. Treble control @  $f_C = 17.5$  kHz.**



### 4.7.2 Center frequency

Figure 16 shows the four possible center frequencies 10 k, 12.5 k, 15 k and 17.5 kHz.


**Figure 16. Treble center frequencies @ gain = 14 dB**



### 4.8 Subwoofer filter

The subwoofer lowpass filter has Butterworth characteristics with programmable cut-off frequency (55 Hz / 85 Hz / 120 Hz / 160 Hz). The output phase can be selected between 0 deg and 180 deg. The input of subwoofer takes signal from bass filter output or output of input mux.

**Figure 17. Subwoofer cut frequencies**




## 4.9 Softstep control

In this device, the softstep function is available for volume, speaker, loudness, treble, middle and bass block. With softstep function, the audible noise of DC offset or the sudden change of signal can be avoided when adjusting gain setting of the block.

For each block, the softstep function is controlled by softstep on/off control bit in the control table. The softstep transient time selection (5 ms or 10 ms) is common for all blocks and it is controlled by softstep time control bit. The softstep operation of all blocks has a common centralized control. In this case, a new softstep operation can not be started before the completion previous softstep.

There are two different modes to activate the softstep operation. The softstep operation can be started right after I<sup>2</sup>C data sending, or the softstep can be activated in parallel after data sending of several different blocks. The two modes are controlled by the 'act bit' (it is normally bit7 of the byte.) of each byte. When act bit is '0', which means action, the softstep is activated right after the date byte is sent. When the act bit is '1', which means wait, the block goes to wait for softstep status. In this case, the block will wait for some other block to activate the operation. The softstep operation of all blocks in wait status will be done together with the block which activate the softstep. With this mode, all specific blocks can do the softstep in parallel. This avoids waiting when the softstep is operated one by one.



## 4.10 DC offset detector

Using the DC offset detection circuit ([Figure 18](#)) an offset voltage difference between the audio power amplifier and the APR's Front and Rear outputs can be detected, preventing serious damage to the loudspeakers. The circuit compares whether the signal crosses the zero level inside the audio power at the same time as in the speaker cell. The output of the zero-window-comparator of the power amplifier must be connected with the WinIn-input of the APR. The WinIn-input has an internal pull-up resistor connected to 5.5 V. It is recommended to drive this pin with open-collector outputs only.

To compensate for errors at low frequencies the WinTC-pin are implemented, with external capacitors introducing the same delay  $\tau = 7.5 \text{ k}\Omega * C_{\text{ext}}$  as the AC-coupling between the APR and the power amplifier introduces. For the zero window comparators, the time constant for spike rejection as well as the threshold are programmable.


For electrical characteristics see [Chapter 3 on page 9](#).

A low-active DC-offset error signal appears at the DCErr output if the next conditions are both true:

- a) Front and rear outputs are inside zero crossing windows.
- b) The Input voltage VWinIn is logic low whenever at least one output of the power amplifier is outside the zero crossing windows.

After power-on, the external attached capacitor is rapidly charged (fast-charge) to overcome a false indication.

Figure 18. DC offset detection circuit (simplified)






### 4.11 Audioprocessor testing

In the test mode, which can be activated by setting bit D7 of the I<sup>2</sup>C subaddress byte and bit D0 of the testing audioprocessor byte, several internal signals are available at the SE1L pin. In this mode, the input resistance of 100 kΩ is disconnected from the pin. Internal signals available for testing are listed in the data-byte specification.

Figure 19. Test circuit




## 5 I<sup>2</sup>C bus specification

### 5.1 Interface protocol

The interface protocol comprises:

- a start condition (S)
- a chip address byte (the LSB determines read/write transmission)
- a subaddress byte
- a sequence of data (N-bytes + acknowledge)
- a stop condition (P)
- the max. clock speed is 400 kbit/s
- 3.3 V logic compatible

Figure 20. I<sup>2</sup>C bus interface protocol




1. S = Start
2. ACK = Acknowledge

### 5.2 I<sup>2</sup>C bus electrical characteristics

Table 6. I<sup>2</sup>C bus electrical characteristics

| Symbol              | Parameter                 | Min | Max | Unit |
|---------------------|---------------------------|-----|-----|------|
| f <sub>SCL</sub>    | SCL clock frequency       | -   | 400 | kHz  |
| V <sub>IH</sub>     | High level input voltage  | 2.4 | -   | V    |
| V <sub>IL</sub>     | Low level input voltage   | -   | 0.8 | V    |
| t <sub>HD,STA</sub> | Hold time for START       | 0.6 | -   | μs   |
| t <sub>SU,STO</sub> | Setup time for STOP       | 0.6 | -   | μs   |
| t <sub>LOW</sub>    | Low period for SCL clock  | 1.3 | -   | μs   |
| t <sub>HIGH</sub>   | High period for SCL clock | 0.6 | -   | μs   |
| t <sub>F</sub>      | Fall time for SCL/SDA     | -   | 300 | ns   |
| t <sub>R</sub>      | Rise time for SCL/SDA     | -   | 300 | ns   |
| t <sub>HD,DAT</sub> | Data hold time            | 0   | -   | ns   |
| t <sub>SU,DAT</sub> | Data setup time           | 100 | -   | ns   |

Figure 21. I<sup>2</sup>C bus data



### 5.2.1 Receive mode

|   |   |   |   |   |   |   |   |     |     |    |   |    |    |    |    |    |    |     |      |     |   |
|---|---|---|---|---|---|---|---|-----|-----|----|---|----|----|----|----|----|----|-----|------|-----|---|
| S | 1 | 0 | 0 | 0 | 1 | 0 | 0 | R/W | ACK | TS | X | AI | A4 | A3 | A2 | A1 | A0 | ACK | DATA | ACK | P |
|---|---|---|---|---|---|---|---|-----|-----|----|---|----|----|----|----|----|----|-----|------|-----|---|

S = Start

R/W = "0" -> Receive Mode (Chip can be programmed by  $\mu$ P)

"1" -> Transmission Mode (Data could be received by  $\mu$ P)

ACK = Acknowledge

P = Stop

TS = Testing mode

AI = Auto increment

### 5.2.2 Transmission mode

|   |   |   |   |   |   |   |   |     |     |   |   |   |   |   |   |   |    |    |     |   |
|---|---|---|---|---|---|---|---|-----|-----|---|---|---|---|---|---|---|----|----|-----|---|
| S | 1 | 0 | 0 | 0 | 1 | 0 | 0 | R/W | ACK | X | X | X | X | X | X | X | BZ | SM | ACK | P |
|---|---|---|---|---|---|---|---|-----|-----|---|---|---|---|---|---|---|----|----|-----|---|

SM = Soft mute activated for main channel

BZ = Softstep Busy ('0' = Busy)

X = Not used

The transmitted data is automatic updated after each ACK. Transmission can be repeated without new chip address.

### 5.2.3 Reset condition

A Power-On-Reset is invoked if the supply voltage is below than 3.5 V. After that the registers are initialized to the default data written in following tables.

Table 7. Subaddress (receive mode)

| MSB |    |    |    |    |    |    | LSB |                                   | Function |
|-----|----|----|----|----|----|----|-----|-----------------------------------|----------|
| I2  | I1 | I0 | A4 | A3 | A2 | A1 | A0  |                                   |          |
| 0   | -  | -  | -  | -  | -  | -  | -   | <b>Testing mode</b><br>Off        |          |
| 1   | -  | -  | -  | -  | -  | -  | -   | On                                |          |
| -   | x  | -  | -  | -  | -  | -  | -   | <b>Not used</b>                   |          |
| -   | -  | 0  | -  | -  | -  | -  | -   | <b>Auto increment mode</b><br>Off |          |
| -   | -  | 1  | -  | -  | -  | -  | -   | On                                |          |
| -   | -  | -  | 0  | 0  | 0  | 0  | 0   | Main selector                     |          |
| -   | -  | -  | 0  | 0  | 0  | 0  | 1   | Not used                          |          |
| -   | -  | -  | 0  | 0  | 0  | 1  | 0   | Not used                          |          |
| -   | -  | -  | 0  | 0  | 0  | 1  | 1   | Not used                          |          |
| -   | -  | -  | 0  | 0  | 1  | 0  | 0   | Soft mute / others                |          |
| -   | -  | -  | 0  | 0  | 1  | 0  | 1   | Soft step I                       |          |
| -   | -  | -  | 0  | 0  | 1  | 1  | 0   | Soft step II / DC-detector        |          |
| -   | -  | -  | 0  | 0  | 1  | 1  | 1   | Loudness                          |          |
| -   | -  | -  | 0  | 1  | 0  | 0  | 0   | Volume / output gain              |          |
| -   | -  | -  | 0  | 1  | 0  | 0  | 1   | Treble                            |          |
| -   | -  | -  | 0  | 1  | 0  | 1  | 0   | Middle                            |          |
| -   | -  | -  | 0  | 1  | 0  | 1  | 1   | Bass                              |          |
| -   | -  | -  | 0  | 1  | 1  | 0  | 0   | Subwoofer / middle / bass         |          |
| -   | -  | -  | 0  | 1  | 1  | 0  | 1   | Speaker attenuator left front     |          |
| -   | -  | -  | 0  | 1  | 1  | 1  | 0   | Speaker attenuator right front    |          |
| -   | -  | -  | 0  | 1  | 1  | 1  | 1   | Speaker attenuator left rear      |          |
| -   | -  | -  | 1  | 0  | 0  | 0  | 0   | Speaker attenuator right rear     |          |
| -   | -  | -  | 1  | 0  | 0  | 0  | 1   | Subwoofer attenuator left         |          |
| -   | -  | -  | 1  | 0  | 0  | 1  | 0   | Subwoofer attenuator right        |          |
| -   | -  | -  | 1  | 0  | 0  | 1  | 1   | Testing audio processor 1         |          |
| -   | -  | -  | 1  | 0  | 1  | 0  | 0   | Testing audio processor 2         |          |
| -   | -  | -  | 1  | 0  | 1  | 0  | 1   | Testing audio processor 3         |          |

### 5.3 Data byte specification

Table 8. Main selector (0)

| MSB |    |    |    | LSB |    |    |    | Function                                                                                          |
|-----|----|----|----|-----|----|----|----|---------------------------------------------------------------------------------------------------|
| D7  | D6 | D5 | D4 | D3  | D2 | D1 | D0 |                                                                                                   |
| -   | -  | -  | -  | -   | 0  | 0  | 0  | <b>Main source selector</b><br>SE1<br>SE3<br><u>QD1</u><br>QD2 / FD1<br>SE2<br>SE4<br>SE5<br>Mute |
|     |    |    |    |     | 0  | 0  | 1  |                                                                                                   |
|     |    |    |    |     | 0  | 1  | 0  |                                                                                                   |
|     |    |    |    |     | 0  | 1  | 1  |                                                                                                   |
|     |    |    |    |     | 1  | 0  | 0  |                                                                                                   |
|     |    |    |    |     | 1  | 0  | 1  |                                                                                                   |
|     |    |    |    |     | 1  | 1  | 0  |                                                                                                   |
|     |    |    |    |     | 1  | 1  | 1  |                                                                                                   |
| -   | -  | -  | -  | 0   | -  | -  | -  | <b>FD / QD2 selection</b><br>FD<br><u>QD2</u>                                                     |
|     |    |    |    | 1   |    |    |    |                                                                                                   |
| -   | -  | -  | 0  | -   | -  | -  | -  | <b>Main source input gain select</b><br>0 dB<br><u>3 dB</u>                                       |
|     |    |    | 1  |     |    |    |    |                                                                                                   |
| -   | -  | 0  | -  | -   | -  | -  | -  | <b>Subwoofer flat</b><br>Off<br><u>On</u>                                                         |
|     |    | 1  |    |     |    |    |    |                                                                                                   |
| x   | x  | -  | -  | -   | -  | -  | -  | <b>Not used</b>                                                                                   |

Not used (1-3)

Table 9. Soft mute / others (4)

| MSB    |        |        |        | LSB              |                  |        |        | Function                                                                  |
|--------|--------|--------|--------|------------------|------------------|--------|--------|---------------------------------------------------------------------------|
| D7     | D6     | D5     | D4     | D3               | D2               | D1     | D0     |                                                                           |
| -      | -      | -      | -      | -                | -                | -      | 0<br>1 | <b>Soft mute</b><br><u>On</u><br><u>Off</u>                               |
| -      | -      | -      | -      | -                | -                | 0<br>1 | -      | <b>Pin influence for mute</b><br><u>Pin and IIC</u><br><u>IIC</u>         |
| -      | -      | -      | -      | 0<br>0<br>1<br>1 | 0<br>1<br>0<br>1 | -      | -      | <b>Soft mute time</b><br>0.48 ms<br>0.96 ms<br>7.68 ms<br><u>15.36 ms</u> |
| -      | -      | -      | 0<br>1 | -                | -                | -      | -      | <b>Subwoofer input source</b><br><u>Input mux</u><br><u>Bass output</u>   |
| -      | -      | 0<br>1 | -      | -                | -                | -      | -      | <b>Subwoofer enable (OUTSWL &amp; OUTSWR)</b><br><u>On</u><br><u>Off</u>  |
| -      | 0<br>1 | -      | -      | -                | -                | -      | -      | <b>Fast charge</b><br><u>On</u><br><u>Off</u>                             |
| 0<br>1 | -      | -      | -      | -                | -                | -      | -      | <b>Anti-alias filter</b><br><u>On</u><br><u>Off (bypass)</u>              |

Table 10. SoftStep I (5)

| MSB    |        |        |        |        |        |        | LSB    |                                                 | Function |
|--------|--------|--------|--------|--------|--------|--------|--------|-------------------------------------------------|----------|
| D7     | D6     | D5     | D4     | D3     | D2     | D1     | D0     |                                                 |          |
| -      | -      | -      | -      | -      | -      | -      | 0<br>1 | <b>Loudness soft step</b><br>On<br><u>Off</u>   |          |
| -      | -      | -      | -      | -      | -      | 0<br>1 | -      | <b>Volume soft step</b><br>On<br><u>Off</u>     |          |
| -      | -      | -      | -      | -      | 0<br>1 | -      | -      | <b>Treble soft step</b><br>On<br><u>Off</u>     |          |
| -      | -      | -      | -      | 0<br>1 | -      | -      | -      | <b>Middle soft step</b><br>On<br><u>Off</u>     |          |
| -      | -      | -      | 0<br>1 | -      | -      | -      | -      | <b>Bass soft step</b><br>On<br><u>Off</u>       |          |
| -      | -      | 0<br>1 | -      | -      | -      | -      | -      | <b>Speaker LF soft step</b><br>On<br><u>Off</u> |          |
| -      | 0<br>1 | -      | -      | -      | -      | -      | -      | <b>Speaker RF soft step</b><br>On<br><u>Off</u> |          |
| 0<br>1 | -      | -      | -      | -      | -      | -      | -      | <b>Speaker LR soft step</b><br>On<br><u>Off</u> |          |

Table 11. SoftStep II / DC detector (6)

| MSB              |                  |                  |                  | LSB    |        |        |        | Function                                                                                                          |
|------------------|------------------|------------------|------------------|--------|--------|--------|--------|-------------------------------------------------------------------------------------------------------------------|
| D7               | D6               | D5               | D4               | D3     | D2     | D1     | D0     |                                                                                                                   |
| -                | -                | -                | -                | -      | -      | -      | 0<br>1 | <b>Speaker RR soft step</b><br>On<br><u>Off</u>                                                                   |
| -                | -                | -                | -                | -      | -      | 0<br>1 | -      | <b>Subwoofer left soft step</b><br>On<br><u>Off</u>                                                               |
| -                | -                | -                | -                | -      | 0<br>1 | -      | -      | <b>Subwoofer right soft step</b><br>On<br><u>Off</u>                                                              |
| -                | -                | -                | -                | 0<br>1 | -      | -      | -      | <b>Soft step time</b><br>5 ms<br><u>10 ms</u>                                                                     |
| -                | -                | 0<br>0<br>1<br>1 | 0<br>1<br>0<br>1 | -      | -      | -      | -      | <b>Zero-comparator window size</b><br>$\pm 100$ mV<br>$\pm 75$ mV<br>$\pm 50$ mV<br><u><math>\pm 25</math> mV</u> |
| 0<br>0<br>1<br>1 | 0<br>1<br>0<br>1 | -                | -                | -      | -      | -      | -      | <b>Spike rejection time constant</b><br>11 $\mu$ s<br>22 $\mu$ s<br>33 $\mu$ s<br><u>44 <math>\mu</math>s</u>     |



Table 12. Loudness (7)

| MSB |    |    |    |    |    |    | LSB |                  | Function |
|-----|----|----|----|----|----|----|-----|------------------|----------|
| D7  | D6 | D5 | D4 | D3 | D2 | D1 | D0  |                  |          |
| -   | -  | -  | -  | 0  | 0  | 0  | 0   | Attenuation      |          |
|     |    |    |    | 0  | 0  | 0  | 1   | 0 dB             |          |
|     |    |    |    | :  | :  | :  | :   | -1 dB            |          |
|     |    |    |    | 1  | 1  | 1  | 0   | -14 dB           |          |
|     |    |    |    | 1  | 1  | 1  | 1   | -15 dB           |          |
| -   | -  | 0  | 0  | -  | -  | -  | -   | Center frequency |          |
|     |    | 0  | 1  |    |    |    |     | Flat             |          |
|     |    | 1  | 0  |    |    |    |     | 400 Hz           |          |
|     |    | 1  | 1  |    |    |    |     | 800 Hz           |          |
|     |    |    |    |    |    |    |     | 2400 Hz          |          |
| -   | 0  | -  | -  | -  | -  | -  | -   | High boost       |          |
|     | 1  |    |    |    |    |    |     | On               |          |
|     |    |    |    |    |    |    |     | Off              |          |
| 0   | -  | -  | -  | -  | -  | -  | -   | Soft step action |          |
| 1   |    |    |    |    |    |    |     | Act              |          |
|     |    |    |    |    |    |    |     | Wait             |          |

Table 13. Volume / output gain (8)

| MSB |    |    |    |    |    |    | LSB |                  | Function |
|-----|----|----|----|----|----|----|-----|------------------|----------|
| D7  | D6 | D5 | D4 | D3 | D2 | D1 | D0  |                  |          |
| -   | -  | 0  | 0  | 0  | 0  | 0  | 0   | Gain/attenuation |          |
|     |    | 0  | 0  | 0  | 0  | 0  | 0   | 1                | +0 dB    |
|     |    | :  | :  | :  | :  | :  | :   | :                | +1 dB    |
|     |    | 0  | 0  | 1  | 1  | 1  | 1   | 1                | :        |
|     |    | 0  | 1  | 0  | 0  | 0  | 0   | 0                | +15 dB   |
|     |    | :  | :  | :  | :  | :  | :   | :                | +16 dB   |
|     |    | 0  | 1  | 0  | 1  | 1  | 1   | 1                | :        |
|     |    | 0  | 1  | 1  | 0  | 0  | 0   | 0                | +23 dB   |
|     |    | :  | :  | :  | :  | :  | :   | :                | Not used |
|     |    | 0  | 1  | 1  | 1  | 1  | 1   | 1                | :        |
|     |    | 1  | 0  | 0  | 0  | 0  | 0   | 0                | Not used |
|     |    | :  | :  | :  | :  | :  | :   | :                | -0 dB    |
|     |    | 1  | 0  | 1  | 1  | 1  | 1   | 1                | :        |
|     |    | :  | :  | :  | :  | :  | :   | :                | -15 dB   |
|     |    | 1  | 1  | 1  | 1  | 1  | 1   | 1                | -31 dB   |
| -   | 0  | -  | -  | -  | -  | -  | -   | Output gain      |          |
|     | 1  |    |    |    |    |    |     | 1 dB             |          |
|     |    |    |    |    |    |    |     | 0 dB             |          |
| 0   | -  | -  | -  | -  | -  | -  | -   | Soft step action |          |
| 1   |    |    |    |    |    |    |     | Act              |          |
|     |    |    |    |    |    |    |     | Wait             |          |

Table 14. Treble filter (9)

| MSB |    |    |    | LSB |    |    |        | Function                                   |              |
|-----|----|----|----|-----|----|----|--------|--------------------------------------------|--------------|
| D7  | D6 | D5 | D4 | D3  | D2 | D1 | D0     |                                            |              |
| -   | -  | -  | 0  | 0   | 0  | 0  | 0      | <b>Gain/attenuation</b><br>-15 dB          |              |
|     |    |    | 0  | 0   | 0  | 0  | 1      | -14 dB                                     |              |
|     |    |    | :  | :   | :  | :  | :      | :                                          | :            |
|     |    |    | 0  | 1   | 1  | 1  | 1      | 0                                          | -1 dB        |
|     |    |    | 0  | 1   | 1  | 1  | 1      | 1                                          | 0 dB         |
|     |    |    | 1  | 1   | 1  | 1  | 1      | 1                                          | 0 dB         |
|     |    |    | 1  | 1   | 1  | 1  | 1      | 0                                          | <u>+1 dB</u> |
|     |    |    | :  | :   | :  | :  | :      | :                                          | :            |
|     |    |    | 1  | 0   | 0  | 0  | 0      | 1                                          | +14 dB       |
|     |    |    | 1  | 0   | 0  | 0  | +15 dB |                                            |              |
| -   | 0  | 0  | -  | -   | -  | -  | -      | <b>Treble center frequency</b><br>10.0 kHz |              |
|     | 0  | 1  |    |     |    |    |        | 12.5 kHz                                   |              |
|     | 1  | 0  |    |     |    |    |        | 15.0 kHz                                   |              |
|     | 1  | 1  |    |     |    |    |        | <u>17.5 kHz</u>                            |              |
| 0   | -  | -  | -  | -   | -  | -  | -      | <b>Soft step action</b><br>Act             |              |
|     |    |    |    |     |    |    |        | 1                                          |              |

Table 15. Middle filter (10)

| MSB |    |    |    | LSB |    |    |        | Function                          |              |
|-----|----|----|----|-----|----|----|--------|-----------------------------------|--------------|
| D7  | D6 | D5 | D4 | D3  | D2 | D1 | D0     |                                   |              |
| -   | -  | -  | 0  | 0   | 0  | 0  | 0      | <b>Gain/attenuation</b><br>-15 dB |              |
|     |    |    | 0  | 0   | 0  | 0  | 1      | -14 dB                            |              |
|     |    |    | :  | :   | :  | :  | :      | :                                 | :            |
|     |    |    | 0  | 1   | 1  | 1  | 1      | 0                                 | -1 dB        |
|     |    |    | 0  | 1   | 1  | 1  | 1      | 1                                 | 0 dB         |
|     |    |    | 1  | 1   | 1  | 1  | 1      | 1                                 | 0 dB         |
|     |    |    | 1  | 1   | 1  | 1  | 1      | 0                                 | <u>+1 dB</u> |
|     |    |    | :  | :   | :  | :  | :      | :                                 | :            |
|     |    |    | 1  | 0   | 0  | 0  | 0      | 1                                 | +14 dB       |
|     |    |    | 1  | 0   | 0  | 0  | +15 dB |                                   |              |
| -   | 0  | 0  | -  | -   | -  | -  | -      | <b>Middle Q factor</b><br>0.75    |              |
|     | 0  | 1  |    |     |    |    |        | 1                                 |              |
|     | 1  | 0  |    |     |    |    |        | <u>1.25</u>                       |              |
|     | 1  | 1  |    |     |    |    |        | Reserved                          |              |
| 0   | -  | -  | -  | -   | -  | -  | -      | <b>Soft step action</b><br>Act    |              |
|     |    |    |    |     |    |    |        | 1                                 |              |

Table 16. Bass filter (11)

| MSB    |    |    |    | LSB |    |    |        | Function                |
|--------|----|----|----|-----|----|----|--------|-------------------------|
| D7     | D6 | D5 | D4 | D3  | D2 | D1 | D0     |                         |
| -      | -  | -  | 0  | 0   | 0  | 0  | 0      | -15 dB                  |
|        |    |    | 0  | 0   | 0  | 0  | 1      | -14 dB                  |
|        |    |    | :  | :   | :  | :  | :      | :                       |
|        |    |    | 0  | 1   | 1  | 1  | 0      | -1 dB                   |
|        |    |    | 0  | 1   | 1  | 1  | 1      | 0 dB                    |
|        |    |    | 1  | 1   | 1  | 1  | 1      | 0 dB                    |
|        |    |    | 1  | 1   | 1  | 1  | 0      | +1 dB                   |
|        |    |    | :  | :   | :  | :  | :      | :                       |
|        |    |    | 1  | 0   | 0  | 0  | 0      | 1                       |
|        |    |    | 1  | 0   | 0  | 0  | +15 dB |                         |
| -      | 0  | 0  | -  | -   | -  | -  | -      | <b>Bass Q factor</b>    |
|        | 0  | 1  |    |     |    |    |        | 1.0                     |
|        | 1  | 0  |    |     |    |    |        | 1.25                    |
|        | 1  | 1  |    |     |    |    |        | 1.5                     |
|        |    |    |    |     |    |    |        | <u>2.0</u>              |
| 0<br>1 | -  | -  | -  | -   | -  | -  | -      | <b>Soft step action</b> |
|        |    |    |    |     |    |    |        | Act                     |
|        |    |    |    |     |    |    |        | <u>Wait</u>             |

Table 17. Subwoofer / middle / bass (12)

| MSB    |    |    |    | LSB |    |    |    | Function                           |
|--------|----|----|----|-----|----|----|----|------------------------------------|
| D7     | D6 | D5 | D4 | D3  | D2 | D1 | D0 |                                    |
| -      | -  | -  | -  | -   | -  | 0  | 0  | <b>Subwoofer cut-off frequency</b> |
|        |    |    |    |     |    | 0  | 1  | 55 Hz                              |
|        |    |    |    |     |    | 1  | 0  | 85 Hz                              |
|        |    |    |    |     |    | 1  | 1  | <u>120 Hz</u>                      |
|        |    |    |    |     |    |    |    | 160 Hz                             |
| -      | -  | -  | -  | -   | 0  | -  | -  | <b>Subwoofer output phase</b>      |
|        |    |    |    |     | 1  |    |    | 180 deg                            |
|        |    |    |    |     |    |    |    | <u>0 deg</u>                       |
| -      | -  | -  | 0  | 0   | -  | -  | -  | <b>Middle center frequency</b>     |
|        |    |    | 0  | 1   |    |    |    | 500 Hz                             |
|        |    |    | 1  | 0   |    |    |    | 1000 Hz                            |
|        |    |    | 1  | 1   |    |    |    | 1500 Hz                            |
|        |    |    |    |     |    |    |    | <u>2500 Hz</u>                     |
| -      | 0  | 0  | -  | -   | -  | -  | -  | <b>Bass center frequency</b>       |
|        | 0  | 1  |    |     |    |    |    | 60 Hz                              |
|        | 1  | 0  |    |     |    |    |    | 80 Hz                              |
|        | 1  | 1  |    |     |    |    |    | 100 Hz                             |
|        |    |    |    |     |    |    |    | <u>200 Hz</u>                      |
| 0<br>1 | -  | -  | -  | -   | -  | -  | -  | <b>Bass DC mode</b>                |
|        |    |    |    |     |    |    |    | On                                 |
|        |    |    |    |     |    |    |    | <u>Off</u>                         |

**Table 18. Speaker attenuation (FL/FR/RL/RR/SWL/SWR) (13-18)**

| MSB |    |    |    | LSB |    |    |    | Function                |
|-----|----|----|----|-----|----|----|----|-------------------------|
| D7  | D6 | D5 | D4 | D3  | D2 | D1 | D0 |                         |
| -   | 0  | 0  | 0  | 0   | 0  | 0  | 0  | 0 dB                    |
|     | 0  | 0  | 0  | 0   | 0  | 0  | 1  | 1 dB                    |
|     | :  | :  | :  | :   | :  | :  | :  | :                       |
|     | 0  | 0  | 0  | 1   | 1  | 1  | 1  | +15 dB                  |
|     | 0  | 0  | 1  | 0   | 0  | 0  | 0  | -0 dB                   |
|     | 0  | 0  | 1  | 0   | 0  | 0  | 1  | -1 dB                   |
|     | :  | :  | :  | :   | :  | :  | :  | :                       |
|     | 1  | 0  | 1  | 1   | 1  | 1  | 1  | -78 dB                  |
|     | 1  | 0  | 1  | 1   | 1  | 1  | 1  | -79 dB                  |
| 1   | 1  | 1  | x  | x   | x  | x  | x  | <u>mute</u>             |
| 0   | -  | -  | -  | -   | -  | -  | -  | <b>Soft step action</b> |
| 1   | -  | -  | -  | -   | -  | -  | -  | Act<br><u>Wait</u>      |

**Table 19. Testing audio processor 1 (19)**

| MSB |    |    |    | LSB |    |    |    | Function                                            |
|-----|----|----|----|-----|----|----|----|-----------------------------------------------------|
| D7  | D6 | D5 | D4 | D3  | D2 | D1 | D0 |                                                     |
| -   | -  | -  | -  | -   | -  | -  | 0  | <b>Audio processor testing mode</b>                 |
|     |    |    |    |     |    |    | 1  | <u>Off</u><br>On                                    |
| -   | -  | -  | 0  | 0   | 0  | 0  | -  | <b>Test multiplexer at SE1L <sup>(1)</sup></b>      |
|     |    |    | 0  | 0   | 0  | 1  |    | SSCLK                                               |
|     |    |    | 0  | 0   | 1  | 0  |    | REQ                                                 |
|     |    |    | 0  | 0   | 1  | 1  |    | SMCLK                                               |
|     |    |    | 0  | 1   | 0  | 0  |    | DCDet Vth High                                      |
|     |    |    | 0  | 1   | 0  | 1  |    | DCDet Vth Low                                       |
|     |    |    | 0  | 1   | 1  | 0  |    | IntZeroErr                                          |
|     |    |    | 0  | 1   | 1  | 1  |    | Ref5V5                                              |
|     |    |    | 1  | 0   | 0  | 0  |    | VGB1.95                                             |
|     |    |    | 1  | 0   | 0  | 1  |    | Clock200k                                           |
|     |    |    | 1  | 0   | 1  | 0  |    | SDCLK                                               |
|     |    |    | 1  | 0   | 1  | 0  |    | VrefDCO                                             |
| -   | -  | 0  | -  | -   | -  | -  | -  | <b>Clock fast mode <sup>(2)</sup></b>               |
|     |    | 1  |    |     |    |    |    | On<br><u>Off</u>                                    |
| -   | 0  | -  | -  | -   | -  | -  | -  | <b>Clock source <sup>(2)</sup></b>                  |
|     | 1  |    |    |     |    |    |    | External<br><u>Internal (200 kHz)</u>               |
| 0   | -  | -  | -  | -   | -  | -  | -  | <b>Attenuator gain clock control <sup>(2)</sup></b> |
| 1   |    |    |    |     |    |    |    | On<br><u>Off</u>                                    |

1. The control bit needs both I<sup>2</sup>C test mode on & sub-address test mode on.

2. The control bit does not depend on test mode.

Table 20. Testing audio processor 2 (20)

| MSB |    |    |    |    |    |    | LSB |                                                                                  | Function |
|-----|----|----|----|----|----|----|-----|----------------------------------------------------------------------------------|----------|
| D7  | D6 | D5 | D4 | D3 | D2 | D1 | D0  |                                                                                  |          |
| -   | -  | -  | -  | -  | -  | -  | 0   | Test architecture <sup>(1)</sup><br>Normal<br>Split                              |          |
| -   | -  | -  | -  | -  | -  | -  | 1   |                                                                                  |          |
| -   | -  | -  | -  | -  | -  | 0  | -   | Oscillator clock <sup>(2)</sup><br>400 kHz<br>800 kHz                            |          |
| -   | -  | -  | -  | -  | -  | 1  | -   |                                                                                  |          |
| -   | -  | -  | -  | -  | 0  | -  | -   | Softstep curve <sup>(2)</sup><br>S-Curve<br>Linear curve                         |          |
| -   | -  | -  | -  | -  | 1  | -  | -   |                                                                                  |          |
| -   | -  | -  | 0  | 0  | -  | -  | -   | Manual set busy signal <sup>(1)</sup><br>Auto<br>Auto<br>0<br>1                  |          |
| -   | -  | -  | 0  | 1  | -  | -  | -   |                                                                                  |          |
| -   | -  | -  | 1  | 0  | -  | -  | -   |                                                                                  |          |
| -   | -  | -  | 1  | 1  | -  | -  | -   |                                                                                  |          |
| -   | -  | -  | 0  | 0  | -  | -  | -   | Request for clk generator <sup>(1)</sup><br>Allow<br>Allow<br>Stopped<br>Stopped |          |
| -   | -  | -  | 0  | 1  | -  | -  | -   |                                                                                  |          |
| -   | -  | -  | 1  | 0  | -  | -  | -   |                                                                                  |          |
| -   | -  | -  | 1  | 1  | -  | -  | -   |                                                                                  |          |
| -   | -  | 0  | -  | -  | -  | -  | -   | No DCO spike rejection <sup>(1)</sup><br>On<br>Off                               |          |
| -   | -  | 1  | -  | -  | -  | -  | -   |                                                                                  |          |
| x   | x  | -  | -  | -  | -  | -  | -   | Not used                                                                         |          |

1. The control bit needs sub-address test mode on.

2. The control bit does not depend on test mode.

Table 21. Testing audio processor 3 (21)


| MSB |    |    |    |    |    |    | LSB |                                                   | Function |
|-----|----|----|----|----|----|----|-----|---------------------------------------------------|----------|
| D7  | D6 | D5 | D4 | D3 | D2 | D1 | D0  |                                                   |          |
| -   | -  | -  | -  | -  | -  | -  | 0   | Enable clock for FL/FR/RL/RR/SWL/SWR<br>On<br>Off |          |
| -   | -  | -  | -  | -  | -  | -  | 1   |                                                   |          |
| -   | -  | -  | -  | -  | -  | 0  | -   | Enable clock for volume<br>On<br>Off              |          |
| -   | -  | -  | -  | -  | -  | 1  | -   |                                                   |          |
| -   | -  | -  | -  | -  | 0  | -  | -   | Enable clock for treble and bass<br>On<br>Off     |          |
| -   | -  | -  | -  | -  | 1  | -  | -   |                                                   |          |
| -   | -  | -  | -  | 0  | -  | -  | -   | Enable clock for loudness and middle<br>On<br>Off |          |
| -   | -  | -  | -  | 1  | -  | -  | -   |                                                   |          |
| x   | x  | x  | x  | -  | -  | -  | -   | Not used                                          |          |

## 6 Package information

In order to meet environmental requirements, ST offers these devices in different grades of ECOPACK® packages, depending on their level of environmental compliance. ECOPACK® specifications, grade definitions and product status are available at: [www.st.com](http://www.st.com).

ECOPACK® is an ST trademark.

**Figure 22. TSSOP28 mechanical data and package dimensions**



## 7 Revision history

**Table 22. Document revision history**

| Date        | Revision | Changes          |
|-------------|----------|------------------|
| 21-Oct-2009 | 1        | Initial release. |

**Please Read Carefully:**

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

**UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.**

**UNLESS EXPRESSLY APPROVED IN WRITING BY AN AUTHORIZED ST REPRESENTATIVE, ST PRODUCTS ARE NOT RECOMMENDED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE. ST PRODUCTS WHICH ARE NOT SPECIFIED AS "AUTOMOTIVE GRADE" MAY ONLY BE USED IN AUTOMOTIVE APPLICATIONS AT USER'S OWN RISK.**

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2009 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Philippines - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

[www.st.com](http://www.st.com)